

Problem 1: Quantum Operations

The *Hadamard* gate plays a very prominent role in quantum computation:

$$H = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix}$$

- Prove that H is unitary, i.e. that it satisfies $UU^\dagger = U^\dagger U = I$.
- Prove that H is its own inverse by showing $H^2 = I$ where I is the identity operator.
- Calculate the action of the operator on the vectors:

$$|0\rangle = \begin{pmatrix} 1 \\ 0 \end{pmatrix}, \quad |1\rangle = \begin{pmatrix} 0 \\ 1 \end{pmatrix}, \quad |+\rangle = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 1 \end{pmatrix}, \quad |-\rangle = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ -1 \end{pmatrix}$$

Problem 2: Pauli matrices

Consider the four Pauli matrices:

$$I, \quad Z = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix}, \quad X = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}, \quad Y = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix}.$$

- Prove that for each Pauli matrix σ_i we have $\sigma_i^2 = I$ and $\sigma_i^\dagger = \sigma_i$.
- Show that the Pauli matrices are unitary matrices.
- Show that $Y = iXZ$.
- Show that $HXH = Z$ and $HZH = X$.

Problem 3: Measurement

Consider two quantum states $|L\rangle$ and $|R\rangle$ (eigenvalues of Pauli Y operator):

$$|R\rangle = \frac{1}{\sqrt{2}}(|0\rangle + i|1\rangle)$$
$$|L\rangle = \frac{1}{\sqrt{2}}(|0\rangle - i|1\rangle)$$

- Consider the general quantum state:

$$|\psi\rangle = \psi_0 |0\rangle + \psi_1 |1\rangle$$

What are the probabilities of outcome $|R\rangle$ and $|L\rangle$ if we measure $|\psi\rangle$?

- Show that the states $|L\rangle$ and $|R\rangle$ can be generated from $|0\rangle$ and $|1\rangle$ using the following circuit:

$$|0/1\rangle \text{---} \boxed{H} \text{---} \boxed{R_{\pi/2}} \text{---} |R/L\rangle$$

where

$$R_{\theta} = \begin{pmatrix} 1 & 0 \\ 0 & e^{i\theta} \end{pmatrix}.$$

c. What circuit will allow implementing a measurement on the $|L\rangle$ and $|R\rangle$ basis if our hardware only allows for measurement in the computational basis? Use H and R_{θ} gates.